MSKSEMI 美森科













ESD

TVS

TSS

MOV

GDT

PLED

PESDNC2FD5VB-MS

Product specification



PESDNC2FD5VB-MS

Features

- Transient protection for high-speed data lines
- IEC 61000-4-2 (ESD) ±30kV (Contact)
 ±30kV (Air)

IEC 61000-4-4 (EFT) 40A (5/50 ns)

Cable Discharge Event (CDE)

- Package optimized for high-speed lines
- Ultra-small package (1.0mm×0.6mm×0.4mm)
- Protects one data, control or power line
- Low capacitance
- Low leakage current
- Low clamping voltage
- Each I/O pin can withstand over 1000 ESD

MACHANICAL DATA

- DFN1006package
- Flammability Rating: UL 94V-0
- High temperature soldering guaranteed: 260[°]C/10s
- Packaging: Tape and Reel ♦ Reel size: 7 inch
- MSL1

APPLICATIONS

- Portable Electronics
- Desktops, Servers and Notebooks
- Cellular Phones
- MP3 Ports
- Digital Ports
- Subscriber Identity Module (SIM) card

Reference News

PACKAGE OUTLINE	Bi-directional	Marking
		РВ
DFN1006		



ABSOLUTE MAXIMUM RATING


Symbol	Parameter	Value	Units
V _{ESD}	ESD per IEC 61000-4-2 (Contact) ESD per IEC 61000-4-2 (Air)	±30 ±30	KV
P _{PP}	Peak Pulse Power (8/20µs)	60	W
I _{PP}	Peak Pulse Current (8/20μs)	5	А
Tj	Operating Temperature	-55/+125	$^{\circ}$
T _{STG}	Storage Temperature	-55/+150	${\mathbb C}$


ELECTRICAL CHARACTERISTICS (Tamb=25°C)


Symbol	Parameter	Test Condition	Min	Тур	Max	Units
V _{RWM}	Reverse Stand-Off Voltage				5.0	V
V _{BR}	Reverse Breakdown voltage	l _т =1mA	5.6			V
I _R	Reverse leakage current.	V _{RWM} =5V			1	μA
Vc	Clamping Voltage	I _{PP} =1A, t _P =8/20us I _{PP} =5A, t _P =8/20us			9.5 12	V
CJ	Junction Capacitance	V _R =0V,f=1MHz			15	pF





ELECTRICAL CHARACTERISTICS CURVE


















PACKAGEMECHANICALDATA



Dim	Inches		Millimeters		
Dim	MIN	MAX	MIN	MAX	
Α	0.0125	0.02	0.32	0.52	
В	0.000	0.002	0.00	0.05	
С	0.037	0.043	0.95	1.080	
D	0.022	0.027	0.55	0.680	
Е	0.016	0.024	0.40	0.60	
F	0.008	0.012	0.20	0.30	
Н	0.01	5Тур.	0.40	Тур.	
R	0.001	0.005	0.05	0.15	

Suggested PadLayout



NOTES:

- 1. CONTROLLING DIMENSIONS ARE IN MILLIMETERS (ANGLES IN DEGREES).
- 2. THIS LAND PATTERN IS FOR REFERENCE PURPOSES ONLY. CONSULT YOUR MANUFACTURING GROUP TO ENSURE YOUR COMPANY'S MANUFACTURING GUIDELINES ARE MET.

REELSPECIFICATION

P/N	PKG	QTY
PESDNC2FD5VB-MS	DFN1006	10000



PESDNC2FD5VB-MS

Attention

- Any and all MSKSEMI Semiconductor products described or contained herein do not have specifications that can handle applications that require extremely high levels of reliability, such as life-support systems, aircraft's control systems, or other applications whose failure can be reasonably expected to result in serious physical and/or material damage. Consult with your MSKSEMI Semiconductor representative nearest you before using any MSKSEMI Semiconductor products described or contained herein in such applications.
- MSKSEMI Semiconductor assumes no responsibility for equipment failures that result from using products at values that exceed, even momentarily, rated values (such as maximum ratings, operating condition ranges, or other parameters) listed in products specifications of any and all MSKSEMI Semiconductor products described or contained herein.
- Specifications of any and all MSKSEMI Semiconductor products described or contained herein stipulate the performance, characteristics, and functions of the described products in the independent state, and are not guarantees of the performance, characteristics, and functions of the described products as mounted in the customer's products or equipment. To verify symptoms and states that cannot be evaluated in an independent device, the customer should always evaluate and test devices mounted in the customer'sproducts or equipment.
- MSKSEMI Semiconductor. strives to supply high-quality high-reliability products. However, any and all semiconductor products fail with someprobability. It is possiblethat these probabilistic failures could give rise to accidents or events that could endanger human lives, that could give rise to smoke or fire, or that could cause damage to other property. When designing equipment, adopt safety measures so that these kinds of accidents—or events cannot occur. Such measures include but are not limited to protective circuits anderror prevention circuitsfor safedesign, redundant design, and structural design.
- In the event that any or all MSKSEMI Semiconductor products (including technical data, services) described or contained herein are controlled under any of applicable local export control laws and regulations, such products must not be exported without obtaining the export license from theauthorities concerned in accordance with the above law.
- No part of this publication may be reproduced or transmitted in any form or by any means, electronic or mechanical, including photocopying and recording, or any information storage or retrieval system, or otherwise, without the prior written permission of MSKSEMI Semiconductor.
- Information (including circuit diagrams and circuit parameters) herein is for example only; it is not guaranteed for volume production. MSKSEMI Semiconductor believes information herein is accurate and reliable, but no guarantees are made or implied regarding its use or any infringements of intellectual property rights or other rights of third parties.
- Any and all information described or contained herein are subject to change without notice due to product/technology improvement, etc. Whendesigning equipment, referto the "Delivery Specification" for the MSKSEMI Semiconductor productthat you intend to use.