

# 1N5819W S4


## Schottky Barrier Diode

### FEATURES

- Low Forward Voltage Drop
- Guard Ring Construction for Transient Protection
- Negligible Reverse Recovery Time
- Low Capacitance

### PINNING

PIN	DESCRIPTION
1	Cathode
2	Anode



Top View

Simplified outline SOD-123 and symbol

### MECHANICAL DATA


- Case: SOD-123
- Terminals: Solderable per MIL-STD-750, Method 2026
- Approx. Weight: 16mg/0.00056oz

### Maximum Ratings and Electrical characteristics


Ratings at 25 °C ambient temperature unless otherwise specified.

Parameter	Symbols	1N5819W S4		Units
Peak Repetitive Reverse Voltage	$V_{RRM}$	40		V
RMS reverse voltage	$V_{RMS}$	28		V
Working Peak Reverse Voltage	$V_{DC}$	40		V
Peak Forward Surge Current, 8.3ms single half sine-wave superimposed on rated load (JEDEC method)	$I_{FSM}$	13		A
Maximum Instantaneous Forward Voltage $I_F=20mA$	$V_F$	0.37		V
		0.60		
Power Dissipation	$P_D$	400		mW
Reverse current $V_R=30V$	$I_R$	5		uA
Thermal Resistance, Junction to Ambient Air	$R_{\theta JA}$	300		°C/W
Reverse voltage $I_R=100uA$	$V_{(BR)}$	40		V
Reverse recovery time $I_F=I_R=200mA, I_{rr}=0.1 \times I_R, R_L=100\Omega$	trr	10		ns
Forward Continuous Current	$I_{FM}$	350		mA
Total capacitance $V_R=0V, f=1MHz$	$C_{tot}$	28		pF
Junction temperature	$T_j$	125		°C
Storage temperature	$T_{stg}$	-55 ~ +150		°C


**Fig.1 Power Derating Curve**




**Fig.2 Typical Reverse Characteristics**




**Fig.3 Forward Characteristics**




**Fig.4 Maximum Non-Repetitive Peak Forward Surge Current**



**Fig.5 Typical Junction Capacitance**




**Fig.6 Typical Transient Thermal Impedance**



**PACKAGE OUTLINE**

Plastic surface mounted package; 2 leads

**SOD-123**

**SOD-123 mechanical data**

UNIT		A	C	D	E	E <sub>1</sub>	L <sub>1</sub>	b	A <sub>1</sub>	∠
mm	max	1.3	0.22	1.8	2.8	3.9	0.45	0.7	0.2	9°
	min	0.9	0.09	1.5	2.5	3.6	0.25	0.5	—	
mil	max	51	8.7	71	110	154	18	28	8	9°
	min	35	3.5	59	98	142	10	20	—	

**The recommended mounting pad size**
